# Patient Stations, Crest Replacements for Rauland® Responder® III+



P/N BS800C (Single Stainless Steel Faceplate) BS800CPL (Single Plastic Faceplate) BS300C (Single Stainless Steel Faceplate) BS810C (Single Stainless Steel Faceplate) BS820C (Single Stainless Steel Faceplate)









BS810C

BS300C

## **Technical Specifications**

**ELECTRICAL** 

Voltage Rating: MECHANICAL

Wire Leads

Terminals:

Wife Leads

Mounting: SIZE MEASUREMENTS

Fits on standard single gang back box

Plate:

4.5" x 2.75" (Single Gang)

12 - 14 VDC @ 20 MA

### **Wire Color Comparison Table**

#### BS800C

BS800C

	Rauland® Wire Color	Crest Wire Color
1	Black	Black
2	Brown	Brown
3	Red	Red
4	Orange	Orange
5	Yellow	Yellow
6	Pink	Brown/White
7	Blue	Blue
8	Purple	Purple
9	White	White
10	Grey	Grey
11	Black	Black

#### BS820C and BS810C

	Rauland® Wire Color	Crest Wire Color
1	Black	Black
2	Brown	Brown
3	Red	Red
4	Orange	Orange
5	Yellow	Yellow
6	Pink	Brown/White
7	Blue	Blue
8	Purple	Purple
9	Grey	Grey
10	White	White
11	Black	Black

#### BS820C, BS810C and BS300C

	Rauland® Wire Color	Crest Wire Color
1	Black	Black
2	Brown	Brown
3	Red	Red
4	Orange	Orange
5	Yellow	Yellow
6	Pink	Brown/White
7	Blue	Blue
8	Purple	Purple
9	N/A	Empty
10	N/A	Empty

## **Typical Installation**

- 1. Replace existing station with Crest replacement, referencing the wire color comparison tables shown above
- 2. Always test all nurse call stations for correct operation (including cord out if applicable) before placing into service

Crest Technical Support: 1-800-328-8908

Specifications subject to change without notice. Visit CrestHealthcare.com for additional technical documents.